

MJ-22LRG

Red/Green Combo Exit Sign



Red/Green Combo Exit Sign

The MJ-2 Series LED Exit Sign is designed for reliable emergency egress lighting with enhanced brightness. Featuring a built-in 9.6V rechargeable battery and high-output LED illumination, it ensures clear visibility during power outages. Ideal for commercial and residential applications such as offices, stairwells, hallways, retail spaces, and public buildings.



MJ-22
(Can Switch Colors)

Key Features — Red/Green Combo Exit Sign

- Available in red, green, or dual-color (red/green) lettering
- Built-in 9.6V rechargeable battery
- Minimum 90 minutes emergency operation
- High output: 150 lumens
- Energy-efficient 2.4WLED consumption
- Dual voltage 120/277V input
- Maximum 24-hour recharge time
- Suitable for commercial and residential applications
- UL listed for safety and reliability

Item Number	Length	Width	Height
MJ-22LRG	20.28"	3.94"	1.59"

Technical Summary



Item Number	Description	CCT	Voltage	Emergency Operation	Battery	Recharge Time	Wattage	Lumen
MJ-22LRG	Red/Green Combo Exit Sign	Red/Green/5000K	120/277V	≥90 mins	build-in 9.6V	≤24hrs	2.4W	150LM

Electrical

- Built-in 9.6V rechargeable battery
- Minimum 90 minutes emergency backup time
- Dual voltage input: 120/277V
- Maximum recharge time: ≤24 hours
- Power consumption: 2.4W

Housing

- Durable thermoplastic housing for lightweight and long-lasting performance
- Flame-retardant construction for safety
- Clean and compact design for commercial use

Optics

- High-efficiency LED output with 150 lumens
- Clear, visible exit lettering for emergency conditions
- Uniform illumination for enhanced visibility

Mount

- Universal mounting for wall, ceiling, or end installation
- Compatible with standard junction boxes
- Quick and easy installation





MJ-22LRG Order Sheet

Project Name:	
Prepare By:	
Date:	
Contact/Phone:	

	Item Number	Description
	MJ-22LRG	Red/Green Combo Exit Sign

